

Order Code: XCBT2X1S3P

X1 Batten - 600mm - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Batten fit PIR



General		Electrical	
Luminaire Wattage (W)	11W/13W/15W/18W	Rated Input Current (A)	0.09
Weight (kg)	1.28	Power Factor (pf)	0.83 to 0.92
Operating Temperature (ta °C)	45	Input Voltage Range (VAC)	220 to 240
Light Output		Inrush Current Peak (A)	
Lumens (lm)	1300 to 2300	Surge Protection (kV)	L-N 1KV, LN-PG 2KV
Efficacy (lm/W)	132	Conductor Size (mm)	0.5 to 2.5
LED		Terminal Type	
CRI	85	4 pole piano key	
Macadam Ellipses	5		
Driver			
Driver Current (mA)	200 , 250 , 300 , 350		
Forward Voltage (V)	25 to 57		
Emergency			
Emergency Lumen Operating	264		
Emergency Wattage (W)	2		

Order Code: XCBT2X1S3P

X1 Batten - 600mm - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Batten fit PIR

Dimensions

A (mm)	841
B (mm)	55
C (mm)	58

Line Drawing

