

Product Name: 12V LED STRIP DRIVERS

General information

- This luminaire must be installed in accordance with the latest edition of the IET Wiring Regulations and local Building Regulation by a qualified competent person.
- The mains power supply must be turned off before inspection, installation or removal of the luminaire, ensuring that the supply is locked off to prevent inadvertently switching the supply on.
- It is the installer's responsibility to ensure that the installation is suitable for the total load of the luminaire(s). The supply cable fuses/circuit breakers must be correctly rated for the electrical load and taking into account for any transient inrush currents that may occur.
- It is the installer's responsibility to ensure that the environmental operating and storage conditions are complied with and that any fire risks are considered.
- Do not perform insulation strength or insulation resistance tests on the installation with the luminaire(s) connected, this can damage the luminaires and give erroneous readings.
- Do not loop-in supply cables at the luminaire supply terminals unless there is provision for 2-way connection at the terminals.
- The light source contained in this luminaire must only be replaced by TamLite Lighting or an appointed service agent.
- Emergency lighting luminaires must be installed and maintained in accordance with the emergency lighting standard BS 5266-1.
- To ensure that the product warranty remains valid, the luminaire must be installed and maintained in accordance with these installation instructions and the product must not be modified in any way.




Luminaires marked with this symbol must not be covered with thermally insulating material.



This symbol on covers over light sources indicates dangerous live parts do not operate the luminaire with this cover removed.







Dimensions

	DIMENSIONS			XCITE SINGLE COLOUR STRIP		XCITE RGB STRIP	
	A (mm)	B (mm)	C (mm)	MAXIMUM LENGTH OF SINGLE RUN	MAXIMUM COMBINED LENGTH OF TWO RUN	MAXIMUM LENGTH OF SINGLE RUN	MAXIMUM COMBINED LENGTH OF TWO RUN
XCDRV15	101	40	20	3m	3m	2m	2m
XCDRV30	123	45	19	6m	6m	4m	4m
XCDRV50	149	40	27	10m	10m	7m	7m
XCDRV75	170	45	28	10m	15m	10m	10m



Picture for illustration purpose only.

Product Name: 12V LED STRIP DRIVERS

<p>1</p>  <p>Remove the product from the packaging.</p>	<p>2</p>  <p>Remove the terminal covers from each end of the driver.</p>
<p>3</p>  <p>Connect LED supply wires to the output side of the driver.</p>	<p>4</p>  <p>Connect mains supply to the input side of the driver.</p>
<p>5</p>  <p>Replace the terminal covers from each end of the driver.</p>	<p>6</p>  <p>Secure the driver in an appropriate position.</p>

Page 2 of 2

Tamlite Technical
Stafford Park 12,
Telford, Shropshire,
TF3 3BJ

+44(0)1952 292441
technical@tamlite.co.uk
Document No: V3

