

Order Code: XCEBANM3STEU3

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintained Emergency Self-test

**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit top and rear cable entries BESA for wall fix
- Reduced maintenance and high performance
- EURO 1, 2 and 3 running man legend also available [sold separately]

Construction

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend
- Integral auto self-test for reduced maintenance, includes a disable function
- Supplied with LiFePO4 battery

Technical Data**General**

| | |
|-------------------------------|-----------|
| Luminaire Wattage (W) | 2 |
| Weight (kg) | 1.24 |
| Operating Temperature (ta °C) | 5° to 25° |

Driver

| | |
|---------------------|------|
| Driver Current (mA) | 340 |
| Forward Voltage (V) | 2.49 |

Electrical

| | |
|---------------------------|------------------|
| Rated Input Current (A) | 0.05 |
| Power Factor (pf) | 0.17 |
| Input Voltage Range (VAC) | 220 to 240 |
| Conductor Size (mm) | 1.5 |
| Terminal Type | 3 pole push down |

Order Code: XCEBANM3STEU3

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintained Emergency Self-test

Dimensions

| | |
|--------|-----|
| A (mm) | 392 |
| B (mm) | 190 |
| C (mm) | 60 |

Line Drawing

