

Order Code: XCEBNM3

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit side and rear cable entries BESA for wall fix
- Reduced maintenance and high performance

Construction

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend

Technical Data

General

Luminaire Wattage (W)	1
Weight (kg)	1.39
Operating Temperature (ta °C)	5 to 25

LED

CCT (K)	6500
CRI	60

Driver

Driver Current (mA)	340
Forward Voltage (V)	2.8

Electrical

Power Factor (pf)	0.19
Input Voltage Range (VAC)	220-240
Surge Protection (kV)	1
Conductor Size (mm)	1.5
Terminal Type	Piano Key

Order Code: XCEBNM3

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency

Dimensions

A (mm)	392
B (mm)	190
C (mm)	60

Line Drawing

