

Order Code: XCEDL1NM3CST

1W - Fixed output - Non-maintained Emergency Self-test - Corridor function - 6500K



Features

- Suitable for open areas and escape routes
- Virtually service free emergency lighting
- Easy to install with simple connection wiring

Construction

- Polycarbonate body
- Very low energy consumption - 1W
- Separate high quality LED driver
- Operates in non-maintained mode
- Internal mains connection
- Integral auto self-test for reduced maintenance

Technical Data

General		Electrical	
Luminaire Wattage (W)	1	Rated Input Current (A)	0.035
Weight (kg)	0.36	Power Factor (pf)	0.19
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240
LED		Conductor Size (mm)	1.5
CCT (K)	6500	Terminal Type	3 pole screw down
CRI	70		
Emergency			
Emergency Lumen Operating	140		
Emergency Wattage (W)	1		

Order Code: XCEDL1NM3CST
1W - Fixed output - Non-maintained Emergency Self-test - Corridor function - 6500K

Dimensions

C (mm)	57
Cut Out (mm)	50
Dia. (mm)	60

Line Drawing

