

Order Code: XCEDL1NM3ST

1W - Fixed output - Non-maintained Emergency Self-test - 6500K



Features

- Suitable for open areas and escape routes
- Virtually service free emergency lighting
- Easy to install with simple connection wiring

Construction

- Polycarbonate body
- Very low energy consumption - 1W
- Separate high quality LED driver
- Operates in non-maintained mode
- Internal mains connection
- Integral auto self-test for reduced maintenance



Technical Data

| General | | Electrical | |
|-------------------------------|---------|---------------------------|-------------------|
| Luminaire Wattage (W) | 1 | Rated Input Current (A) | 0.035 |
| Weight (kg) | 0.36 | Power Factor (pf) | 0.19 |
| Operating Temperature (ta °C) | 5 to 25 | Input Voltage Range (VAC) | 220-240 |
| | | Conductor Size (mm) | 1.5 |
| | | Terminal Type | 3 pole screw down |
| LED | | | |
| CCT (K) | 6500 | | |
| CRI | 70 | | |
| Emergency | | | |
| Emergency Lumen Operating | 140 | | |
| Emergency Wattage (W) | 1 | | |

Order Code: XCEDL1NM3ST

1W - Fixed output - Non-maintained Emergency Self-test - 6500K

Dimensions

| | |
|--------------|----|
| C (mm) | 57 |
| Cut Out (mm) | 50 |
| Dia. (mm) | 60 |

Line Drawing

