

Order Code: XCSBT631NWM3

31W - 1800mm Batten - 4000K - 3hrs Maintained Emergency

Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- Batten fit PIR option available
- Up to 131 lumens per watt efficacy

Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral high quality driver and LED module
- Loop in/out mains connector
- Conduit and BESA fixing points for end or rear cable entry
- Available in warm white [3000K], neutral white [4000K] or daylight [6000K]



Technical Data

General

Luminaire Wattage (W)	31
Weight (kg)	1.70
Operating Temperature (ta °C)	5 to 25

Light Output

Lumens (lm)	4050
Efficacy (lm/W)	131

LED

CCT (K)	4000
CRI	80
Macadam Elipses	4

Emergency

Emergency Lumen Operating	190
Emergency Wattage (W)	1

Electrical

Rated Input Current (A)	0.14
Power Factor (pf)	0.9
Input Voltage Range (VAC)	220-240
Inrush Current Peak (A)	10
Surge Protection (kV)	1
Conductor Size (mm)	1.5
Terminal Type	4 pole piano key

Order Code: XCSBT631NWM3

31W - 1800mm Batten - 4000K - 3hrs Maintained Emergency

Dimensions

A (mm)	1800
B (mm)	55
C (mm)	58
Fix	610

Line Drawing

