

Order Code: XCBLC8CT

8W - Downlight BL CC - CCTK Selector [3000K/4000K/6000K]- Fixed output



Features

- Suitable for general domestic and commercial use
- CCT selectable via selector switch [3000K/4000K/6000K]
- Available in 6 sizes
- Available in 6 different outputs
- Phase cut dimming option available
- 3 hours emergency maintained with compatible conversion box [Emergency Kit](#)
- Up to 88 lumens per watt efficacy

Construction

- Frosted polycarbonate diffuser



Technical Data

General		Electrical	
Luminaire Wattage (W)	8	Rated Input Current (A)	0.04
Weight (kg)	0.12	Power Factor (pf)	0.96
Operating Temperature (ta °C)	0 to 25	Input Voltage Range (VAC)	198-264
Light Output		Inrush Current Peak (A)	1
Lumens (lm)	700	Surge Protection (kV)	1
Efficacy (lm/W)	88	Conductor Size (mm)	0.75 - 1.5 mm ²
LED		Terminal Type	PUSH BUTTON 2
CCT (K)	3000K/4000K/6000K		
CRI	80		
Macadam Elipses	4		
Driver			
Driver Current (mA)	200		
Forward Voltage (V)	27-42		

Order Code: XCBLC8CT

8W - Downlight BL CC - CCTK Selector [3000K/4000K/6000K]- Fixed output

Dimensions

C (mm)	26
Cut Out (mm)	100
Dia. (mm)	120

Line Drawing

