

**Order Code: XCBLC8CT**

8W - Downlight BL CC - CCTK Selector [3000K/4000K/6000K]- Fixed output



**Features**

- Suitable for general domestic and commercial use
- CCT adjustable via 3-way selector switch [3000K/4000K/6000K]
- Available in 6 sizes
- Available in 6 different outputs
- Phase cut dimming option available
- 3 hours emergency maintained with compatible conversion box [Emergency Kit](#)
- Up to 88 lumens per watt efficacy

**Construction**

- Frosted polycarbonate diffuser



**Technical Data**

General		Electrical	
Luminaire Wattage (W)	8	Rated Input Current (A)	0.04
Weight (kg)	0.12	Power Factor (pf)	0.96
Operating Temperature (ta °C)	0 to 25	Input Voltage Range (VAC)	198-264
<b>Light Output</b>		Inrush Current Peak (A)	1
Lumens (lm)	700	Surge Protection (kV)	1
Efficacy (lm/W)	88	Conductor Size (mm)	0.75 - 1.5 mm <sup>2</sup>
<b>LED</b>		Terminal Type	PUSH BUTTON 2
CCT (K)	3000K/4000K/6000K		
CRI	80		
Macadam Ellipses	4		
<b>Driver</b>			
Driver Current (mA)	200		
Forward Voltage (V)	27-42		

**Order Code:** XCBLC8CT

8W - Downlight BL CC - CCTK Selector [3000K/4000K/6000K]- Fixed output

### Dimensions

C (mm)	26
Cut Out (mm)	100
Dia. (mm)	120

### Line Drawing

