

Order Code: XCEBAM3ST

XCITE EXIT BOX ST XCEBA 3W - 6500K - Fixed output - Emergency Self-test

**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit top and rear cable entries BESA for wall fix
- Reduced maintenance and high performance
- EURO 1, 2 and 3 running man legend also available [sold separately]

Construction

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend
- Integral auto self-test for reduced maintenance, includes a disable function
- Supplied with LiFePO4 battery

Technical Data**General**

Luminaire Wattage (W)	3
Weight (kg)	1.24
Operating Temperature (ta °C)	5° to 25°

Driver

Driver Current (mA)	340
Forward Voltage (V)	2.57

Electrical

Rated Input Current (A)	0.05
Power Factor (pf)	0.25
Input Voltage Range (VAC)	220 to 240
Conductor Size (mm)	1.5
Terminal Type	4 pole push down

Order Code: XCEBAM3ST

XCITE EXIT BOX ST XCEBA 3W - 6500K - Fixed output - Emergency Self-test

Dimensions

A (mm)	392
B (mm)	190
C (mm)	60

Line Drawing

