# xcite LED Lighting

## **Data Sheet**



Order Code: XCEBANM3ST

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintainted Emergency Self-test

#### Features











### **Technical Data**

| General                       |           | Electrical                |                  |
|-------------------------------|-----------|---------------------------|------------------|
| Luminaire Wattage (W)         | 2         | Rated Input Current (A)   | 0.05             |
| Weight (kg)                   | 1.24      | Power Factor (pf)         | 0.17             |
| Operating Temperature (ta °C) | 5° to 25° | Input Voltage Range (VAC) | 220 to 240       |
| Driver Driver Current (mA)    |           | Conductor Size (mm)       | 1.5              |
|                               | 340       | Terminal Type             | 3 pole push down |
| Forward Voltage (V)           | 2.49      |                           |                  |

# xcite LED Lighting

## **Data Sheet**



### Order Code: XCEBANM3ST

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintainted Emergency Self-test

#### **Dimensions**

| A (mm) | 392 |
|--------|-----|
| B (mm) | 190 |
| C (mm) | 60  |

### Line Drawing



