

Order Code: XCFRATX1
X1 FRD TILT - 2700K-6000K + Wattage Switchable



Features

- Suitable for domestic applications
- Ideal for retrofit of existing halogen downlight fixtures
- 30, 60 & 90 minute fire rating with solid timber joists
- 30 minute fire rating with Staircraft I-Joist and METAL WEB Joist [Compatibility Matrix]
- CCT [2700K,3000K,4000K,6000K] adjustable via 4-way selector switch
- Wattage [4W,6W] adjustable via 2-way selector switch
- Up to 20° tilt adjustment for flexible aiming
- Dimmable as standard

Construction

- Thermally-insulating material coverable
- Easy accessible CCT and Wattage switches beneath magnetic fix bezel for quick and simple adjustment
- 2-part loop in/out push-fit terminal block for quick installation

Installation Notes

Screwless terminals for quick & easy installation

Technical Data

General		Electrical	
Luminaire Wattage (W)	4W/6W	Rated Input Current (A)	0.02 to 0.03
Weight (kg)	0.15	Power Factor (pf)	0.88
Operating Temperature (ta °C)	5° to 25°	Input Voltage Range (VAC)	220 to 240
Light Output		Inrush Current Peak (A)	160
Lumens (lm)	340 to 610	Surge Protection (kV)	1KV
Efficacy (lm/W)	93	Conductor Size (mm)	0.5 to 2.5
LED		Terminal Type	3 pole piano key
CCT (K)	2700K to 6000K		
CRI	80		
Macadam Elipses	0.8 to 6.9		
Driver			
Driver Current (mA)	11mA to 17mA		
Forward Voltage (V)	250		

Order Code: XCFRATX1
X1 FRD TILT - 2700K-6000K + Wattage Switchable

Dimensions

C (mm)	56
Cut Out (mm)	84
Dia. (mm)	99

Line Drawing

